

Stromsensoren

CDS4000

Produkt abgekündigt.
Nicht für Neuentwicklungen zu verwenden.



1. Anlieferform

Die Sensoren werden in vakuumverpackten ESD-konformen Trays angeliefert. Mit einem leeren Tray werden die obersten Sensoren abgedeckt. Maximal 2 beladene Trays bilden eine Verpackungseinheit (VE).



Abb. 1: In Trays verpackte CDS4000.



Abb. 2: Vakuumverpackte CDS4000.

2. Lagerbedingungen

Vakuumverpackt können die Sensoren, limitiert durch den Temperaturbereich der verwendeten Trays, zeitlich unbegrenzt bei -20°C bis +80°C gelagert werden.

Die Sensoren sind mindestens 2 Tage vor der Weiterverarbeitung bei 5° - 30°C zu lagern. Nach Öffnung der Verpackung sind die Sensoren bei 5° - 30°C und max. 60% relativer Luftfeuchte 5 Tage verarbeitbar (ähnlich MSL 3/4). Werden die 5 Tage offener Lagerung überschritten, kann durch Trocknen der Sensoren bei 80°C für 24h und anschließendem Verschweißen der ursprüngliche Lagerzustand wiederhergestellt werden.

Aufgrund der magnetischen Empfindlichkeit des Sensors ist die unmittelbare Umgebung des Lagerortes frei von Magnetfeldern zu halten, die stärker sind als 50 mT (z. B. Dauermagnete in Motoren).

3. Verarbeitungsbedingungen

Es handelt sich um ESD-empfindliche Bauteile. Die allgemeinen ESD-Sicherheitsmaßnahmen sind einzuhalten.

Die Verwendung von lösemittelhaltigen Reinigungsmitteln kann zum Verlust der Sensorbeschriftung führen.

Aufgrund der magnetischen Empfindlichkeit der Sensoren ist auf die Verwendung von Werkzeugen, die Magnetfelder stärker als 50 mT emittieren (z.B. magnetische Schraubendreher), in unmittelbarer Nähe der Sensoren zu verzichten.

Manuelles Löten ist nur an den Signalpins zulässig. Das in der Bauteilspezifikation vorgegebene Lötprofil (< 7sec @ 260°C) ist einzuhalten, ohne die Signalpins oder den Sensor mechanisch zu belasten. Es wird empfohlen, für diesen Fall die Leiterplatte auf <100°C vorzuheizen.



DIE NICHTBEACHTUNG EINES ODER MEHRERER DER VORSTEHENDEN HINWEISE KANN ZUM VERLUST DER GEWÄHRLEISTUNG FÜHREN. EINE HAFTUNG VON SENSITEC GMBH FÜR DIE HIERAUS ENTSTEHENDEN FOLGEN IST EBENFALLS AUSGESCHLOSSEN.

General Information

Disclaimer

Sensitec GmbH reserves the right to make changes, without notice, in the products, including software, described or contained herein in order to improve design and/or performance. Information in this document is believed to be accurate and reliable. However, Sensitec GmbH does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information. Sensitec GmbH takes no responsibility for the content in this document if provided by an information source outside of Sensitec products.

In no event shall Sensitec GmbH be liable for any indirect, incidental, punitive, special or consequential damages (including but not limited to lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) irrespective the legal base the claims are based on, including but not limited to tort (including negligence), warranty, breach of contract, equity or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, Sensitec product aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the General Terms and Conditions of Sale of Sensitec GmbH. Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Unless otherwise agreed upon in an individual agreement Sensitec products sold are subject to the General Terms and Conditions of Sales as published at www.sensitec.com.

Application Information

Applications that are described herein for any of these products are for illustrative purposes only. Sensitec GmbH makes no representation or warranty – whether expressed or implied – that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using Sensitec products, and Sensitec GmbH accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the Sensitec product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

Sensitec GmbH does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using Sensitec products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s).

Sensitec does not accept any liability in this respect.

Life Critical Applications

These products are not qualified for use in life support appliances, aeronautical applications or devices or systems where malfunction of these products can reasonably be expected to result in personal injury.

Copyright © 2018 by Sensitec GmbH, Germany

All rights reserved. No part of this document may be copied or reproduced in any form or by any means without the prior written agreement of the copyright owner. The information in this document is subject to change without notice. Please observe that typical values cannot be guaranteed. Sensitec GmbH does not assume any liability for any consequence of its use.

Sensitec GmbH

Georg-Ohm-Str. 11 · 35633 Lahnau · Germany
Tel. +49 6441 9788-0 · Fax +49 6441 9788-17
www.sensitec.com · sensitec@sensitec.com

