

## Current Sensor

---

Product Series: STK-BS/T

Part number: STK-200BS/T & STK-400BS/T &  
STK-500BS/T & STK-600BS/T &  
STK-800BS/T & STK-1000BS/T &  
STK-1200BS/T & STK-1500BS/T

VERSION: Ver 2.4



---

## CONTENT

1.	Introduction .....	2
2.	Electrical Data .....	3
3.	Dimension & Pin Definitions .....	5

## 1. Introduction

STK-BS/T series current sensor is based on Hall, and it has an open-loop design. It is suitable for DC, AC pulsed and any kind of irregular current measurement under the isolated conditions.

### Typical applications

- Battery supplied applications
- Motor driver
- Electric welder power supply
- UPS

### General parameter

Parameter	Symbol	Unit	Value
Working temperature	T <sub>A</sub>	°C	-40 ~ 85
Storage temperature	T <sub>stg</sub>	°C	-40 ~ 85
Mass	m	g	300

### Absolute maximum rating

Parameter	Symbol	Unit	Value
Supply voltage (not-destructive)	V <sub>CC</sub>	V	± 18
ESD rating (HBM)	U <sub>ESD</sub>	kV	4

Remark: the unrecoverable damage may occur when the product works on the conditions over the absolute maximum ratings. Long-time working on the absolute maximum ratings may cause the degradation on performance and reliability.

### Isolation parameter

Parameter	Symbol	Unit	Value	Comment
RMS voltage for AC test 50Hz/1 min	U <sub>d</sub>	kV	4.9	
Clearance distance (pri. -sec)	d <sub>Cl</sub>	mm	11	Shortest distance through air
Creepage distance (pri. -sec)	d <sub>Cp</sub>	mm	11	Shortest path along device body
Case material			V0 according to UL 94	

## 2. Electrical Data

 Condition:  $T_A = 25^{\circ}\text{C}$ ,  $V_{CC} = \pm 12 \sim \pm 15\text{V}$ 

Parameter	Symbol	Unit	Min	Typ	Max	Comment
Primary nominal current	$I_{PN}$	A		200		STK-200BS/T
				400		STK-400BS/T
				500		STK-500BS/T
				600		STK-600BS/T
				800		STK-800BS/T
				1000		STK-1000BS/T
				1200		STK-1200BS/T
				1500		STK-1500BS/T
Current range (refer remark)	$I_{PM}$	A	-600		600	STK-200BS/T
			-1200		1200	STK-400BS/T
			-1500		1500	STK-500BS/T
			-1800		1800	STK-600BS/T
			-2400		2400	STK-800BS/T
			-2500		2500	STK-1000BS/T
			-2500		2500	STK-1200BS/T
			-2500		2500	STK-1500BS/T
Supply voltage	$V_{CC}$	V		$\pm 12 \sim \pm 15$		STK-200BS/T STK-400BS/T STK-500BS/T STK-600BS/T STK-800BS/T STK-1000BS/T STK-1200BS/T STK-1500BS/T
Current consumption	$I_{CC}$	mA		$\pm 20$		All
Quiescent voltage $V_{out} @ 0\text{A}$	$V_{off}$	V	-0.04	0	0.04	STK-200BS/T STK-400BS/T STK-500BS/T STK-600BS/T STK-800BS/T STK-1000BS/T STK-1200BS/T STK-1500BS/T
Peak output voltage $(V_{out} @ \pm I_{PN}) - V_{off}$	$V_{FS}$	V		$\pm 4$		STK-200BS/T STK-400BS/T STK-500BS/T STK-600BS/T

						STK-800BS/T STK-1000BS/T STK-1200BS/T STK-1500BS/T
Internal output resistance	R <sub>out</sub>	Ω		100		V <sub>out</sub>
Theoretical gain (Typ)	G <sub>th</sub>	mV/A		20		STK-200BS/T
				10		STK-400BS/T
				8		STK-500BS/T
				6.66		STK-600BS/T
				5		STK-800BS/T
				4		STK-1000BS/T
				3.33		STK-1200BS/T
				2.66		STK-1500BS/T
Rated linearity error	Non-L	% I <sub>PN</sub>		± 1		±I <sub>PN</sub>
Step response time	t <sub>res</sub>	μs		5		@90% of I <sub>PN</sub>
Frequency bandwidth (-3dB)	BW	kHz		25		No RC circuit
Output voltage noise DC ~ 10 kHz DC ~ 100 kHz	V <sub>noise</sub>	mV <sub>pp</sub>		20		STK-200BS/T STK-400BS/T STK-500BS/T STK-600BS/T STK-800BS/T STK-1000BS/T STK-1200BS/T STK-1500BS/T
				30		
Accuracy @ 25°C	X	% of I <sub>PN</sub>		± 1		All
Temperature coefficient of V <sub>OE</sub>	TCV <sub>OE</sub>	mV/K		± 1		@ -40°C ~ 85°C
Temperature coefficient of V <sub>OUT</sub>	TCV <sub>OUT</sub>	%/K		± 0.1		@ -40°C ~ 85°C

### 3. Dimension & Pin Definitions

